# NxxxH Series Current Sensor

The NxxxH series is a current transducer which operates on the principle of magnetic compensation. It measures DC, AC or pulse currents and their combinations, with galvanic isolation techniques used to separate the



#### Features

- Non-contact measurement of high current
- Close-Loop measurement (compensated)
- Max. measuring range ±200A (DC or AC peak)
- Nearly zero magnetic hysteresis
- Superior temperature stability and linearity
- High frequency bandwidth typ. 150kHz
- RoHs compliance (Lead-Free)

#### Applications

- Home appliances
- AC variable speed drives and servo motor drives
- Static converters for DC motor drives
- Battery management systems
- Uninterruptible power supplies (UPS)
- Switched-mode power supplies (SMPS)
- Overcurrent protections
- Short circuit protections

#### Advantages

- Accurately measures AC, DC and pulse currents
- Fast response < 0.5µs
- High immunity from external interference
- Excellent current overload capacity

#### Standards

- EN 61000-4 Series
- IEC60068-2 Series
- EN 50178: 1998
- IEC62109-1: 2010
- IEC61800-3: 2017
- IEC61800-5-1: 2016

- 1 -

## Absolute maximum ratings

Symbol	Parameter	Min.	Max.	Unit
V <sub>DD Max</sub> .	Maximum supply voltage (not destructive)	-15	15	V
I <sub>Pm</sub>	Maximum measuring current	-200	200	A
T <sub>A</sub>	Ambient operating temperature	-40	85	°C
Ts	Storage temperature range	-40	100	°C
V <sub>ESD-HB</sub> m	ESD sensitivity HBM (Human Body Model)	4	8	kV

Stresses above these ratings may cause permanent damage. Exposure to absolute maximum ratings for extended periods may degrade reliability.

# Specifications ( $T_A = 25^{\circ}C$ , $V_{DD} = \pm 15.0V$ )

Symbol	Parameter	п50н	N502H	піоон	N1002H	N125H	N1252H	Unit
V <sub>DD</sub>	Supply voltage	±1215						V
Ic	Current consumption @I_=0 without $I_{c\varepsilon}$	<10						mA
$\mathbf{I}_{PN}$	Current nominal measuring range	±50	±50	±100	±100	±125	±125	A
I <sub>PM</sub>	Current maximum measuring range	±90	±150	±150	±180	±200	±200	A
K <sub>n</sub>	Conversion ratio	1:1,000	1:2,000	1:1,000	1:2,000	1:1,000	1:2,000	
<b>I</b> <sub>sn</sub>	Secondary nominal rms current	±50	±25	±100	±50	±125	±75	mA
Rs	Coil resistance @25 °C	< 30	< 100	< 30	< 100	< 30	< 100	Ω
T <sub>CIOT</sub>	Temperature coefficient of $I_{\mbox{\scriptsize out}}$ @-40°C85 °C	±0.3 Typ./ ±0.15 Typ./ ±0.3 Typ./ ±0.3 Typ./ ±0.15 Typ.// ±0.15 Ty						mA
ε	Non-linearity error $\textcircled{0}{\mathbb E} I_{\text{PN}}$ without offset	<0.1	<0.1	<0.1	<0.1	<0.1	<0.1	%/I <sub>PN</sub>
I <sub>OE</sub>	Offset current @I <sub>P</sub> =0	±0.2	±0.1	±0.2	±0.1	±0.2	±0.1	mA
T <sub>RA</sub>	Step response to 10% of $I_{\mbox{\scriptsize PN}}$	<0.3						μs
Ť <sub>R</sub>	Step response to 90% of $\mathrm{I}_{\mathrm{PN}}$	<0.5						μs
BW	Frequency bandwidth (-3dB)	150						kHz
di/dt	di/dt accurately followed	>100					A/µs	

- 2 -

## **Insulation characteristics**


Symbol	Parameter	Value	Unit	Comment
V <sub>D</sub>	Insulation voltage for isolation, 50Hz, 1 min	3,000	V	
R <sub>iso</sub>	Isolation resistance @500VDC	>500	mΩ	


## **General characteristics**


Symbol	Parameter	Value	Unit	Comment
т-нระ	Housing material	VO		Flame retardant UL 94
m-cdt	Conductor material	H62		Busbar version
M-FC	Flux collector material	Permalloy		Superior magnetic permeability

# Dimension (mm)


#### N100, N1002H, N125H, N1252H







N50H, N502H



18April2023/Version 1.5

# **Name Guide Description**

	<u>n</u>	XX	X	X	X
Series					
N: Close-Loop current sensor					
Nominal range ———					
50: ± 50A 100: ± 100A 125: ± 125A					
Output type					
Null: 1 : 1,000 2: 1 : 2,000					
Mount type					
Null: Thru-Hole PCB mount B: Bus-Bar PCB mount					
Extra Code					

#### Extra Code

### **Notes**

The content of this document is subject to revision without notice. Luksens shall have no liability for any error or damage of any kind resulting from the use of this document.

# Safety and Environment



The product is to be installed by manufacturer trained personnel or competent person trained in accordance with manufacturer installation instructions.

With respect to applicable standards IEC 61010-1/EN 61010-1 safety requirements for electrical equipment for measurement, control and laboratory use part 1 general requirements, the product should be used in limited energy secondary circuits.



### **Risk of electrical shock**

Certain parts of the module can carry hazardous voltage during the operation process of the product because hazardous live voltage of primary conductor, power supply occurs, injury and/or serious damage will be caused if this warning is ignored.

Conducting parts must be inaccessible after installation of the product. Additional protection including shield or protective housing could be used according to IEC 60664 Insulation coordination for equipment within lowvoltage supply systems.

Disconnection of the main supply will protect against possible injury and serious damage.



### **ESD** protection

Damage from an ESD event will occur if the personnel is not well grounded when handling.

### **Important notice**

Luksens reserves the right to make changes to or discontinue any product or service identified in this publication without notice. Luksens advises its customers to obtain the latest version of the relevant information to verify, before placing any orders. The information included herein is believed to be accurate and reliable. However, since additional design, measure, production, quality control take effect in the end product, therefore Luksens shall have no liability for any potential hazards, damages, injuries or less of life resulting from the end product. Luksens products are not to be used in any equipment or system, including but not limited to life support equipment or systems, where failure of Luksens products may cause bodily harm.

- 6 -